

Gasoline Inverter Generator

2.2 KW

RH-4793

- 114cc, 4-stroke high power 2.5kw engine with outstanding performance
- Decreasing weight more than 20% compared with normal gasoline generator for better portability and less occupation
- Produces Output Pure Sine Wave AC and stable voltage to prevent from damaging to sensitive electronics equipment such as cell phone, laptop, and TV etc
- Super quiet as low as 58 DBA
- Equiped with two 220V AC outlet and one 12V DC outlet
- Economy Mode Switch Reduces wear and fuel consumption by adjusting RPM based on generator load
- The control unit instantly senses overload or short circuit and immediately shuts of engine to protect the generator and the load
- Low Oil Alert Helps to prevent engine damage
- deal for electronics equipment, RV, camping and home applications, small power tools



Model	RH-4793	
Generator	Type	Inverter Generator
	AC Voltage	220V/50Hz
	Max. Output	2.2 KW
	Rated Output	2 KW
	Power Factor	1
	DC Output	DC12V 5A
Engine	Model	XY156F
	Type	Air-cooled, 4 cycle, OHV, Gasoline Engine
	BorexStroke mmxmm	56x46
	Displacement	114cc
	Max. Output	2.5KW / 4500rpm
	Fuel	Gasoline
	Fuel tank Capacity	4.1 liters



	Rated Continuous Operation	3.5 hr
	Lubricating oil	SAE 10W30
	Lubricating oil Capacity	0.52 liter
	Starting System	Recoil Starter
	Ignition system	CDI
	Spark Plug Type	A5RTC
Dimension	Net dimension LxWxH	525x282x457mm
	Overall dimension LxWxH	555x310x490mm
	Net Weight	18.5Kg
	Gross Weight	21Kg
Supplied in	two color carton	
Include	SPARK PLUG SOCKET/ SCREW DRIVER/ BATTERY CHARGE CABLE	